A METHOD AND APPARATUS FOR DETERMINING THE CONTENT OF BURSTS
TO BE TRANSMITTED FROM A BASE STATION

TECHNICAL FIELD

5   The present invention relates generally to a method
and apparatus for determining the content of bursts to be
transmitted on a broadcast frequency from a base station. In
particular, the invention is intended to enable accurate
identification of a base station when measuring a received
10   signal, and to avoid burst confusion.

BACKGROUND OF THE INVENTION AND PRIOR ART
        A mobile communication network includes a plurality
of base stations being connected together by means of
15   switching nodes, such as Base Station Controllers (BSC),
Mobile Switching Centres (MSC), and Serving GPRS (General
Packet Radio Service) Support Nodes (SGSN). Each base
station provides radio coverage over an area known as a
cell, for radio communication with mobile terminals located
20   therein. The mobile network has been allowed to use a
certain limited radio frequency spectrum for transmissions
between base stations and mobile terminals. Thus, data is
transmitted over various logical channels on physical
frequency channels within the allocated spectrum.
25   In a typical cellular network configuration, each
cell is allocated a number of specified physical frequency
channels to be used for call connections and for
broadcasting information to mobile terminals. Since the
total number of available physical frequency channels is
30   limited, they must be reused to some extent in plural cells
throughout the network. However, frequency channels can only
be reused in cells being sufficiently distant from each

other, as to not interfere too much with each other,
although mobile terminals and base stations are adapted to
cope with a certain extent of interference.

5   Cell planners are concerned with allocating
frequencies to the cells in networks where certain reuse
patterns are employed, which is generally well-known in the
art. Great efforts are made to be able to employ tight reuse
patterns, i.e., with as short reuse distances as possible,
in order to maximize the traffic capacity in the network. An
10   important factor to consider is to keep transmission power
levels for calls and broadcasts as low as possible, without
jeopardising the radio coverage, in order to reduce the
amount of interference, which will in turn enable short
reuse distances. Highly accurate power control mechanisms
15   for ongoing calls have therefore been developed.

          Another area of interest is the selection of the
most appropriate base station for connection with a mobile
terminal. For example, if a mobile terminal being connected
to a serving base station moves away from that base station
20   towards a neighbouring base station, the received signal
strength or link quality of the old base station will
decrease and that of the new base station will increase. As
a result, the new base station may become more suitable for
connection, requiring less transmission power to achieve
25   acceptable link quality.

          There are various known mechanisms for switching
connection from a serving base station to a new one,
referred to as "handover" or "handoff" when the terminal is
in busy mode, i.e., engaged in a call, and "cell selection"
30   or "cell reselection" when in idle mode, i.e., not engaged
in a call but powered-on. Switching of serving base station
may also be performed for mobile terminals being in a

packet-switched transfer mode (in contrast to circuit-
switched communication). For either mode, this will
hereafter be referred to as "base station selection" for
simplicity. Hence, correct base station selections will
result in low interference and make tight reuse patterns
possible, as well as saving battery consumption in the
terminals.

In most cellular networks of today, mobile
terminals are required to make measurements on signals from
neighbouring base stations as well as from the serving base
station, and to report the measurement results to the
serving base station. Reported measurements can then be used
by the network for different purposes, such as:

1) Supporting the process of selecting the most
appropriate base station for a specific connection, as
discussed above. The reported measurements on signals from
neighbouring base stations, as well as from the serving base
station, are compared, and the "best" base station is
selected for connection, preferably after some predefined
threshold condition also has been fulfilled. In the case of
handover in busy mode, these measurements are often referred
to as MAHO (Mobile Assisted Handover) measurements.

2) Supporting mechanisms for determining the
position of the terminal (generally called "positioning"),
requiring timing and/or signal strength information of
received signals from each target base station. The terminal
can measure and report the reception delay and/or signal
strength of signals from preferably at least three base
stations. From this information and by the known location of
each base station, the current position of the terminal can
be calculated.

3) Characterising network properties, such as calculating cell relations and evaluating different cell patterns or plans and various algorithms and parameters that are used for operating the network. Various measurements of link quality from different base stations can form a basis for network planning and network configuration work. Cell relations include, e.g., an estimated level of interference if the cells are allocated the same or adjacent frequency channels for transmissions. Typical network planning tasks include: setting cell patterns and transmission power levels, making antenna adjustments and setting frequency allocation parameters and handover thresholds.

From the above, it is evidently desirable that mobile terminals can make accurate and reliable measurements on signals transmitted from different base stations. The impact of reported inaccurate or misleading measurements can thus affect the above-mentioned activities adversely.

In order to enable such measurements, each base station continuously transmits a signal at a fixed power level on at least one broadcast frequency or pilot channel, which in GSM is called the BCCH (Broadcast Control Channel) frequency. Mobile terminals present in the network can then make measurements on the broadcasted signal with respect to, e.g., link quality or timing estimation.

As is well-known, a broadcast frequency includes successive signal bursts transmitted in timeslots. A plurality of logical channels are multiplexed onto the physical broadcast frequency according to a specific TDMA (Time Division Multiple Access) frame structure. The logical channels may include point-to-multipoint channels such as paging channels PCHs, a frequency correction channel (FCCH), a synchronisation channel (SCH), as well as other specific

control channels. The logical channels may also include
dedicated point-to-point traffic channels (TCH), which can
be used for mobile terminal connections, and point-to-point
signalling channels, e.g. a Stand alone Dedicated Control

5   Channel (SDCCH).

        When a mobile terminal connects to a certain base
station, that base station will transmit a measurement order
including a list of broadcast channels transmitted by
neighbour base stations to be measured by the terminal. Such

10   a neighbour list may be pre-defined for each cell, at least
for the purpose of MAHO measurements, and indicates the
broadcast frequency of each target base station and possibly
also the identity of the base station. The number of base
stations included in a neighbour list is typically in the

15   range of 10-32, depending on cell configurations in the
network.

        To illustrate this measuring procedure, Fig. 1
shows a schematic view of a mobile terminal 10 operating in
a cellular communication network 12, including a plurality

20   of base stations 14, 16a-c interconnected by means of a
switching network 18. In this case, the terminal 10 is
currently connected to a serving base station 14. Initially,
when the terminal 10 starts the connection with the serving
base station 14, the terminal 10 receives from the network,

25   by means of the base station 14, a measurement order
including a neighbour list with the broadcast frequencies
(and optionally also identities) of a plurality of
predetermined neighbouring base stations, of which three are
shown, 16a-c. The terminal 10 is thereby ordered by the

30   network to perform measurements, e.g. with respect to link
quality or timing, on the specified broadcast frequencies
during idle periods, and to send one or more reports to the

serving base station 14 and the network. Such reports may be sent in response to polling from the network, or according to a predetermined schedule either specified by the standard used, or by the measurement order that was sent from the

5   network.

Alternatively, the terminal 10 may as yet be unconnected to any serving base station, like for example when the terminal 10 has just been powered on. The terminal then scans for broadcast frequencies and measures them in

10   order to register with a base station having the strongest/best signal.

As mentioned above, mobile terminals may measure broadcasted signals with respect to link quality or timing. Link quality may be measured as at least one of: a received

15   signal strength (RSS), a carrier-to-interference power ratio (C/I), a carrier power, a Bit Error Rate (BER) or any other link quality related parameter. Timing may be measured by detecting a burst offset in relation to a given clock reference provided from the serving base station. However,

20   the present invention is not limited to any particular measuring methods or schedules.

However, due to the above-mentioned co-channel interference problems, measurement errors may occur if the frequency reuse distances are relatively short. The terminal

25   may for example erroneously measure a strong signal from a base station not being an intended target base station but reusing the same broadcast frequency. Furthermore, the measured signal is typically the sum of plural signals transmitted from several sources reusing the same frequency,

30   including their reflections, and the total measured signal strength and/or quality may therefore be misleading.

In some networks, it is therefore required that the terminal must qualify a measurement by verifying the target base station being measured, before reporting the measurement to the serving base station. By ascribing a

5   certain measurement to a certain base station, that measurement will be more reliable, whereas if the terminal fails to identify the base station, the measurement should be discarded.

In WO 02/096149, a solution is disclosed for mobile

10   terminals to accurately ascribe measurements to specific base stations. The measurements are qualified only when their identity can be determined based on the same received signal being measured.

In order to enable identification of base stations,

15   it has been proposed to include in the broadcasted signal from each base station an indication of that base station's identity which the terminal can read, or at least detect. Base station identification is typically further helped by the terminal knowing, from the received neighbour list,

20   which target base station to expect for each measured frequency. In GSM, a base station identity is used called the Base Station Identity Code (BSIC), which is included in the SCH. The BSIC comprises a Network Colour Code (NCC) and a Base station Colour Code (BCC). Furthermore, normal bursts

25   transmitted on the BCCH frequency may contain information which is related to the BSIC, such that the receiving terminal can derive the BSIC therefrom.

In general, transmitted signals have been more or less corrupted during their propagation, when received by

30   the terminal. A process called channel estimation is therefore typically used by the terminal receiver to recover the transmitted signal. Channel estimation utilizes a

training bit sequence known to the terminal, which in the

GSM case is 26 bits long, typically embedded in all normal

bursts transmitted from base stations, including bursts in

the broadcast channel. Exceptions from "normal" bursts may

5   be the FCCH burst which only contains a sinus wave for

frequency synchronisation, and the SCH burst which contains

a longer specific training sequence used for initial TDMA

burst synchronisation. There are numerous known techniques

for channel estimation available, which will not be

10   described here further. In timeslots where there is no

useful information to transmit, so-called "dummy bursts"

containing no data are transmitted, in order to maintain the

required continuous transmission on the BCCH frequency.

Fig. 2 illustrates schematically an exemplary

15   normal burst 20 transmitted in a timeslot of a broadcast

frequency channel from a target base station included in the

neighbour list received by the terminal. The normal burst 20

may belong to any one of many possible logical channels,

e.g. a traffic burst belonging to a traffic channel, and

20   includes a bit field 22 with a training sequence, often

arranged approximately in the middle of the burst. The burst

20 may further include various fields placed on both sides

24, 26 of the training sequence, such as a header field,

fields with payload or control data, tail bit fields etc.

25   The training sequence in a normal burst from a

serving base station is known by the terminal, and is used

to facilitate synchronisation and the decoding or detection

of the burst. A set of known training sequences have

typically been defined, e.g., eight different sequences in

30   GSM, and the one used in a particular burst is identified by

a Training Sequence Code (TSC) of, e.g., 3 bits. In a GSM

common control channel, the TSC is identical to the BCC, and

for other channels, the TSC is communicated in channel
assignment messages to the terminal.

   According to WO 02/096149, the base station
identity is preferably related to the TSC in a way that is
5   known in advance by mobile terminals, by applying "base
station specific" training sequences. A mobile terminal
receiving a normal burst from a target base station can
therefore determine the base station identity, regardless of
which logical channel the received burst belongs to, by
10   detecting an expected training sequence in the burst and
deriving the TSC therefrom. In the simplest case, the base
station identity, such as the BCC in GSM, is set to be
identical with the TSC. However, other relationships are
possible.

15   In WO 02/096149, it is further proposed that
channel estimation is conducted for measured signals from
neighbouring base stations, in order to verify the target
base station. Moreover, channel estimation may be conducted
for several candidate training sequences, in order to
20   separate contributions from plural base stations reusing the
same frequency, as well as any reflections thereof. This
procedure will facilitate detection of the target base
station, which is described in more detail in WO 02/096149.

   In some mobile networks, different modulation
25   methods are used for conveying data bits in the bursts. In
networks using EDGE (Enhanced Data rates for GSM/TDMA136
Evolution) technology, i.e. GERAN (GSM/EDGE Radio Access
Network), two different modulations are used, namely GMSK
(Gaussian Minimum Shift Keying) using two phase positions in
30   each symbol to represent one bit (1 or 0), and 8PSK (8-ary
Phase Shift Keying) using eight phase positions in each
symbol to represent three bits (1 or 0 each). In GERAN,

eight different training sequences with corresponding TSCs
have been defined for each modulation form, where each TSC
is coupled to one GMSK training sequence and to one 8PSK
training sequence, respectively. These training

5   sequences/TSCs have also been stored in mobile terminals
capable of operating in GERAN.

Base stations reusing the same broadcast frequency
can have different BCCs, and by coupling the TSCs to the
BCCs, the training sequences will be different as long as

10   the BCCs are different. This is the case, e.g., in GERAN
base stations supporting a positioning technique called
Enhanced Observed Time Difference (E-OTD). Hence, if a
mobile terminal can recognize the training sequence included
in a received burst, the sending base station can be

15   identified from the TSC/BCC derived from that training
sequence. Here, the terminal may make an estimation attempt
for each possible modulation form on the same received
signal, likewise described further in WO 02/096149. However,
synchronisation bursts, frequency correction bursts and

20   dummy bursts on the broadcast frequency have no base station
specific training sequences, but all other logical channel
bursts should contain one of the above-described base
station specific training sequences.

At least for measurements intended for base station

25   selection purposes, it is important that each base station
continuously transmit on the broadcast frequency, even in
timeslots that are currently unused (i.e. where there is no
data to transmit), to enable measurements at any time.
Unused timeslots may occur in the broadcast frequency frame

30   structure, e.g., when there are unoccupied traffic channels
due to low traffic load, or when so-called discontinuous
transmission (DTX) is currently applied for an occupied

traffic channel, which is a well-known algorithm for minimising interference. In DTX, no data is transmitted when not necessary, e.g. due to silence at the sender side. In cellular networks, it is a general practice to transmit

5   dummy bursts on broadcast frequency channels in unused timeslots, as mentioned above, in order to maintain continuous transmission.

Normally, a "traditional" dummy burst carries no intelligible information, and a predetermined and fixed bit

10   pattern is typically transmitted in all dummy bursts, easily recognizable to mobile terminals. Therefore, it is not possible to determine any base station identity from such dummy bursts, which may sometimes occur quite frequently. Synchronisation bursts and frequency correction bursts occur

15   at fixed frame positions known by mobile terminals, but the occurrence of dummy bursts is more or less unpredictable to them. Moreover, the fixed bit pattern in the entire burst requires special treatment by mobile terminals, since the normal training sequence is not included as expected. Hence,

20   the occurrence of dummy bursts have rendered measurements on neighbouring base stations more difficult.

To overcome these problems, it has been proposed to include in dummy bursts transmitted over broadcast frequency channels, an indication of the base station identity, such

25   as a training sequence which is related to the base station identity in a known way. This will therefore significantly increase the possibilities for mobile terminals to determine the identity of the neighbouring base station having sent a received dummy burst, and to make successful measurements to

30   support, e.g., base station selection and positioning activities.

If a known base station specific training sequence is included in a received dummy burst, the terminal can use it to identify the base station as well as to, e.g. in E-OTD, estimate the timing offset to the corresponding base

5   station, or better estimate the link quality of the burst.

Even though dummy bursts with base station specific training sequences would enable identification of neighbouring base stations, another problem will arise in that the dummy bursts could be erroneously interpreted by

10   mobile terminals as their regular traffic bursts in some situations. For example, if a mobile terminal is active in a call, but the used downlink traffic channel is currently in DTX mode, i.e. the corresponding time slots are unused, the base station must transmit dummy bursts instead to satisfy

15   the continuous broadcasting requirement. Mobile terminals can easily distinguish normal traffic bursts from the traditional dummy bursts with their specific bit pattern, which has very low cross correlation with the training sequences in regular traffic bursts, and correctly interpret

20   such dummy bursts as a continued DTX mode. On the other hand, if a transmitted dummy burst would include a base station specific training sequence instead, it could potentially be erroneously interpreted by the terminal as a regular traffic burst having the same training sequence.

25   If one or more such dummy bursts are interpreted as traffic bursts, the terminal may erroneously believe that the DTX mode is finished and that a speech frame has been received. In that case, the terminal will attempt to decode the error correcting code of the supposed speech frame.

30   Further, it will attempt to decode an error detecting code (also known as a Cyclic Redundancy Check (CRC) code) of the speech frame, to check whether it is a valid speech frame.

Although the error detecting code in most cases gives a
correct indication of whether a speech frame is valid or
not, it is still possible that an invalid frame is
incorrectly deemed to be valid. The probability that an

5   invalid speech frame is interpreted as valid depends on the
number of bits used for the CRC. Typically, this probability
decreases exponentially with an increasing number of CRC
bits. If an invalid speech frame is delivered to the speech
decoder in the terminal, this results in unwanted noise.

10   This problem is especially relevant for the TCH/FS (Traffic
Channel/Full rate Speech) and TCH/HS (Traffic Channel/Half
rate Speech) channels, carrying speech frames adapted to the
early speech codecs of GSM, where only three CRC bits are
used. A three bit CRC means that approximately 1/8-th of the

15   invalid frames are interpreted as valid by the CRC.

The potential problem of misinterpreting traffic
bursts would most likely supersede the benefits gained for
the identification and measuring activities, and therefore
has to be taken into account when introducing dummy bursts

20   with base station specific training sequences.

To conclude, it is of great importance to obtain
reliable measurements on neighbour base stations with high
accuracy, and to minimise the delay time between such
measurements and corresponding reports, in order to improve

25   procedures of base station selection, position determination
and network evaluation. At the same time, it is desirable to
avoid, as far as possible, the risk of misinterpretation of
different bursts received by mobile terminals. It is also
desirable to reduce the impact of interference on the

30   measurement accuracy, thereby allowing for a tighter
frequency reuse.

SUMMARY OF THE INVENTION

The object of this invention is to reduce or
eliminate the problems outlined above. It is an object to
determine the content in bursts to be transmitted from a
5   base station in a mobile network on a broadcast frequency,
such that the risk of burst confusion for connected
terminals is minimised, at the same time burst detection for
measuring terminals is facilitated maximally. It is another
object to determine the burst content such that when dummy
10   bursts are transmitted, mobile terminals can identify the
transmitting base station. It is another object to reduce
interference in the network, as well as the impact of
interference on the measurement accuracy, thereby allowing
for a tighter frequency reuse in the network.

15   These objects and others are obtained by providing
a method and apparatus for determining the content in bursts
to be transmitted from a base station in a mobile network on
a broadcast frequency in specific timeslots of a broadcast
frequency frame structure, wherein a logical channel is
20   allocated to each timeslot. Information is first received on
a forthcoming burst to be transmitted, and a current state
is checked of the logical channel allocated to the
forthcoming burst. The content in the forthcoming burst is
then determined depending on the current channel state, such
25   that a dummy burst with a base station specific training
sequence is transmitted if there is no data to transmit, and
if the dummy burst cannot be confused with a regular traffic
burst according to the current channel state. The dummy
burst to be transmitted has data fields containing no
30   intelligible information to mobile terminals.

A dummy burst with a base station specific training
sequence may be transmitted if the channel is not occupied,

wherein no connected mobile terminal is listening to the channel. If at least two different modulation forms, including GMSK modulation, can be used for the broadcast frequency, the dummy burst may be a GMSK modulated dummy

5   burst. The transmitted dummy burst may belong to a dummy frame in the form of a fill frame generated at a higher layer in the network, such as a Layer 2 fill frame.

      If only a single modulation form can be used for the broadcast frequency, a dummy burst with a common fixed

10   bit pattern may be transmitted, if the channel is occupied but there is no data to transmit. On the other hand, if at least two different modulation forms can be used for the broadcast frequency, a dummy burst with a base station specific training sequence may be transmitted using a

15   modulation form other than the one currently used for the allocated logical channel, if the channel is occupied but there is no data to transmit. If GMSK modulation and 8PSK modulation can be used for the broadcast channel, a GMSK modulated dummy burst may be transmitted, if 8PSK modulation

20   is currently used for the logical channel, or vice versa.

      When a dummy burst is to be transmitted having a base station specific training sequence, the transmitted dummy burst may include a fixed bit pattern located in the burst on at least one side of the base station specific

25   training sequence. Preferably, the fixed bit pattern has, at least partly, a low cross correlation to all possible training sequences defined in the network. The transmitted dummy burst may further include a fixed bit pattern located in the burst on at least one side of the base station

30   specific training sequence, wherein the fixed bit pattern is related to that training sequence in a known manner. If at least two different modulation forms can be used for the

broadcast frequency, the fixed bit pattern may be different
for the different modulation forms.

For systems using DTX, any DTX mode may further be
disabled for logical channels not applying frequency hopping
5   with the broadcast frequency included in the hopping scheme,
such that regular traffic bursts are transmitted even during
silent periods.

BRIEF DESCRIPTION OF THE DRAWINGS
10 The present invention will now be described in more detail
and with reference to the accompanying drawings, in which:
-   Fig. 1 is a schematic view of a mobile communication
    network where measurements on neighbouring base stations
    are performed.
15 -   Fig. 2 is a schematic illustration of an exemplary normal
    burst.
-   Fig. 3 is a schematic illustration of a mobile network
    including a base station transmitting bursts, which can
    be determined in accordance with the invention.
20 -   Fig. 4 is a flow chart illustrating the steps executed in
    a procedure for deciding whether to use DTX for a traffic
    channel.
-   Fig. 5 is a flow chart illustrating the steps executed in
    a procedure for determining the content of bursts to be
25   transmitted, in accordance with the invention.
-   Fig. 6 is a schematic illustration of a dummy burst
    according to one embodiment.
-   Fig. 7 is a schematic illustration of a dummy burst
    according to another embodiment.
30

DESCRIPTION OF PREFERRED EMBODIMENTS

In Fig. 3, three base stations 300a, 300b and 300c are shown belonging to a mobile network (not shown), where the base stations 300a-c are all connected to a base station control node 302, such as a BSC in GSM, which is adapted to

5   control transmissions from the base stations 300a-c by means of a logic unit 304. In the figure, base station 300a is schematically illustrated in more detail, comprising an antenna 306, a multiplexer 308 and a logic unit 310.

The base station is adapted to continuously

10   transmit bursts 312 on a broadcast frequency carrier 314 in successive timeslots according to a TDMA frame structure, of which only a small part is indicated in the figure. For example in GSM, the multi-frame structures for the BCCH frequency define how the logical channels are mapped onto

15   the physical channels. The logic unit 310 in that base station 300a, or alternatively the logic unit 304 in the control node 302, or both, may determine the content in bursts to be transmitted from the base station 300a.

The base stations are of course further equipped

20   with many other necessary components, such as transceivers, filters etc., although not shown here for simplicity. Moreover, the base stations may also transmit from their antennas further physical channels on other carrier frequencies than the broadcast frequency, by using a

25   combiner etc., according to well-known techniques which are not described here further.

The timeslots in each TDMA frame are associated with specific logical channels C1, C2, C3… which can be any type of channels transmitted on a broadcast frequency. The

30   logic unit 310 receives information, not shown, on what is to be transmitted in the respective logical channels, and accordingly creates bit patterns to be transmitted in

successive timeslots. The created bit patterns are then fed
to the multiplexer 308 for sequential transmission as bursts
from the antenna 306 according to the given multi-frame
structure of the broadcast channel. If the logic unit 310

5   receives no data to transmit, a dummy burst may be created
and transmitted, which will be described in more detail
below. Hence in this concept, the logic unit will also be
informed (in GSM, by the BSC) whenever there is no data to
transmit.

10   In the illustrated example, the base station 300a
transmits data in channels C1 and C2 as "normal" bursts,
i.e. containing some sort of received data. However, no data
is to be sent in the channel allocated to the next timeslot
and a dummy burst D is transmitted instead. Next, channels

15   C4, C5 and C6 require that data is sent in their respective
timeslots, but a dummy burst D is transmitted in the next
timeslot due to lack of data to send, and so forth. As
mentioned in the background section, the transmission of
traditional dummy bursts with a common fixed bit pattern may

20   cause problems in some situations, which the present
invention is intended to avoid.

         The present invention is directed to a solution
where the content in a burst to be transmitted, of a
specific logical channel, is determined depending on the

25   current state of that logical channel. In particular, dummy
bursts are transmitted in a way that they cannot be confused
with regular traffic bursts. In the context of the present
invention, a "dummy burst" may be any type of burst with
data fields containing no intelligible or meaningful data to

30   mobile terminals.

         As discussed above, the use of DTX may give rise to
burst confusion in certain situations. When a logical

channel is occupied but its timeslots are currently unused,
meaning that a mobile terminal is connected but there is
currently no data to transmit, a DTX mode is normally
applied. Applying the DTX mode may be decided anywhere in

5   the transmission path depending on the implementation, but
it is most typically decided by a network node controlling
base stations, such as the BSC in GSM systems. During DTX,
the connected terminal is listening to a particular timeslot
in the frame structure allocated to the traffic channel, in

10   order to detect when regular traffic bursts interrupt the
DTX mode. Generally speaking, DTX would not have any
interference saving effect if frequency hopping is not
applied to the broadcast frequency, i.e. when the traffic
channel is transmitted only on the broadcast frequency, due

15   to the continuous transmission requirement for that
frequency. However, if frequency hopping is applied, a DTX
mode would reduce the interference for the other frequencies
used in the hopping scheme. Therefore, the following
procedure illustrated in Fig. 4 is preferably executed in

20   order to minimise interference.

In a first step 400, the properties of a specific
traffic channel transmitted on the broadcast frequency are
checked with respect to frequency hopping. In a next step
402, it is determined whether frequency hopping is applied

25   for that channel. If not, any DTX mode is disabled, or
simply not applied, for that channel due to the continuous
transmission requirement, in a step 404. As a result,
regular traffic bursts will be transmitted in unused
timeslots, i.e. when there is no data to send. In a speech

30   call, such a transmitted traffic burst could contain data
describing silence, optionally including some "comfort
noise", instead of using DTX. This data will be decoded by

the receiver and the perceived effect will be the same to
the user of the receiving terminal anyway, since in DTX a
comfort noise in typically generated locally in the
terminal, often based on received noise parameters, which is
5   well-known in the art. As mentioned above, DTX cannot be
used for the broadcast frequency to reduce interference due
to the continuous transmission requirement, so there is no
disadvantage in disabling the DTX mode to transmit a regular
traffic burst in this situation.

10   On the other hand, if frequency hopping is applied
for that traffic channel, DTX can advantageously be applied
in a step 406, since that would reduce the interference for
the other frequencies used in the hopping scheme. However,
dummy bursts are transmitted instead on the broadcast
15   frequency for that channel in unused timeslots, i.e. during
DTX periods, which will be described below.

             Fig. 5 is a flow chart illustrating a procedure of
determining the content in bursts to be transmitted from a
base station, which is valid for base stations configured to
20   either use a single modulation form for the broadcast
channel, e.g. GMSK as in traditional GSM networks, or
multiple modulation forms, in this case GMSK and 8PSK as in
GERAN.

             The procedure of Fig. 5 is executed each time a
25   traffic channel burst is to be transmitted. In this example,
other logical channels are disregarded, such as various
point-to-point or point-to-multipoint control channels. In a
first step 500, information is received, e.g. in logic unit
310 or 304 of Fig. 3, regarding what data is to be sent, if
30   any, in a next traffic channel burst. This could be specific
payload or control data to be transmitted, or an indication
that there is no data to transmit. In a next step 502, the

state of the traffic channel allocated to the forthcoming
burst is checked. In the following procedure, the burst
content is dependent on the current channel state, as will
be described below.

5   After step 502, it is determined in a step 504
whether the timeslot is unused or not. If it is currently
used and there is data to transmit to a connected mobile
terminal listening to that particular timeslot in the frame
structure, a regular traffic burst is naturally transmitted
10   containing the required data, in a step 506. Of course, all
regular traffic bursts include a base station specific
training sequence, as shown in Fig. 2, enabling proper
identification of the base station.

           If it is determined in step 504 that the timeslot
15   is unused, it is determined in a next step 508 whether the
present channel is currently occupied by an ongoing
connection or not. If it is not occupied, a dummy burst
having a base station (BS) specific training sequence (TS)
is transmitted in the timeslot, in a step 510. Since the
20   channel is unoccupied, no connected terminal is currently
listening to that particular timeslot in the frame
structure, and therefore such a dummy burst with the base
station specific training sequence cannot be mistaken for
being a regular traffic burst by any terminal.

25   In practice, the transmission of dummy bursts in
unoccupied timeslots may also be realised by generating
dummy frames in the form of fill frames, at higher layers in
the network. These fill frames can typically have the same
format as the frames of normal speech or control channels,
30   and are therefore treated as such by the base station. To a
base station, a fill frame for a speech channel would appear
to be a normal speech frame, and therefore the corresponding

dummy bursts would look like any normal traffic bursts with base station specific training sequences. The data in these frames, however, would be neither directed to, nor detected by, any particular mobile terminal. An example of such fill

5   frames are the "Layer 2 fill frames", which in GSM are transmitted in unoccupied signalling blocks on the BCCH channel and Common Control Channel (CCCH).

If the base station is configured to use both GMSK modulation and 8PSK modulation, the dummy burst of step 510

10   is preferably GMSK modulated to further facilitate burst detection for any measuring terminals. For neighbour cell measurement purposes, GMSK modulation is generally to be preferred over 8PSK modulation for the following reasons. 8PSK modulated signals have a higher peak-to-average power

15   than GMSK modulated signals, which means that the maximum power supported by the base station is typically lower for the 8PSK modulated signals. Depending on the nominal output power setting for the cell, 8PSK modulated signals may be transmitted with a reduced average power, resulting in

20   greater uncertainties for link quality and timing measurements, as compared to GMSK. In addition, if an interference rejection algorithm, such as the SAIC (Single Antenna Interference Cancellation, defined in 3GPP TSG GERAN, GP-022891, Work Item for Single Antenna Interference

25   Cancellation, Nov. 2002), is used by connected terminals, a larger gain is generally provided for GMSK interference than for 8PSK interference. Also, the constant envelope properties of the GMSK modulated signals could be utilised to further improve robustness towards interference, which

30   cannot readily be done for 8PSK modulated signals, since they do not possess such properties.

If is determined in step 508 that the present channel is occupied, the following steps will depend on whether the base station is configured to use a single modulation form for the broadcast channel (arrow to the right), or multiple modulation forms, in this case GMSK and 8PSK (arrow downwards).

When a single modulation form is used, a dummy burst with a common fixed bit pattern, i.e. no base station specific training sequence, should be transmitted in a next step 512, such as the previously used traditional dummy burst. The risk of burst confusion with a regular traffic burst by the connected mobile terminal is then avoided. Moreover, when frequency hopping is applied for the traffic channel, DTX can safely be used for this traffic channel in other non-broadcast frequencies included in the hopping scheme, to reduce interference, as decided in step 406 of Fig. 4, since the dummy burst is transmitted anyway regardless of DTX on the broadcast frequency.

It should be noted that in this case (step 512), no dummy burst with a base station specific training sequence should be transmitted, since there is a risk that such a burst could be mistaken as a regular traffic burst by the connected mobile terminal occupying the channel.

If the base station is configured to use multiple modulation forms, it is determined in the next step 514, after step 508, which one of two different modulation forms is used for the present traffic channel. In this example, the base station is configured to use both GMSK and 8PSK modulation, such as EDGE-capable base stations in GERAN. 8PSK provides a higher bit rate with three bits per symbol as compared with one bit per symbol in GMSK, but 8PSK modulated bursts are more sensitive to background

interference and noise, and therefore put higher demands on
the link quality. Hence, the network is free to select the
most appropriate modulation form for a session depending on
link quality and bandwidth requirements of the session. The
5   modulation form may further be switched dynamically during
an ongoing session if the situation changes. It should be
noted that the present invention is not limited to any
particular types or number of modulation forms, or network
types.

10   For base stations using a single modulation form
(arrow to the right), a dummy burst with a common fixed bit
pattern was transmitted in step 512 in order to avoid burst
confusion, although at the cost of making neighbour
measurements on that burst more difficult, as explained
15   above. However, if different modulation forms can be used
(arrow downwards) it is possible to transmit dummy burst
with a base station specific training sequence, and still
avoid burst confusion, in the following manner.

            After step 508, it is checked which modulation form
20   is currently applied to the present channel, in step 514. If
GMSK modulation is currently applied, a dummy burst with a
base station specific training sequence is transmitted in a
step 516, using 8PSK modulation. On the other hand, if 8PSK
modulation is currently applied, a dummy burst with a base
25   station specific training sequence is transmitted in a step
518, using GMSK modulation. By transmitting such dummy
bursts using another modulation form than the one currently
applied, the confusion risk is minimised for the connected
mobile terminal, since the cross correlation between
30   training sequences of the two modulation forms is very low.
Hence, the connected mobile terminal will not interpret,
e.g., a GMSK dummy burst as an 8PSK traffic burst, or vice

versa, even if the training sequence code (TSC) is the same,
since the training sequences are in fact different in the
different modulations.

Generally speaking, a dummy burst with a base
5   station specific training sequence is transmitted using a
modulation form other than the one currently used for the
allocated logical channel. In some specific cases, it may
however be preferable to transmit 8PSK modulated dummy
bursts for logical channels otherwise using GMSK modulation,
10   but not the other way round.

After the burst has been prepared for transmission
in the above-described manner, the process can be repeated
by returning to step 500, to handle the next forthcoming
traffic burst to be transmitted, and so forth.

15   In the cases where dummy bursts with base station
specific training sequences are to be transmitted, as in the
above steps 510, 516 and 518, the results mentioned above
can be further improved by selecting suitable bit patterns
before and after the actual training sequence in the burst.

20   Fig. 6 illustrates schematically one embodiment of
a dummy burst 600 having a base station specific training
sequence 602 approximately in the middle of the burst,
although in practice it may be located anywhere in the
burst. On either side of the training sequence 602, a fixed
25   bit pattern 604a and 604b, respectively, is included. At
least one of the two patterns, preferably both, has a low
cross correlation, i.e. low similarity, to all possible
training sequences used in the network (eight per modulation
form in the case of GSM/GERAN), including the present one
30   602 which is specific for the transmitting base station.
Thereby, the risk is minimised that these parts of the burst
are erroneously interpreted as a training sequence by mobile

terminals, either connected or just measuring. Alternatively, the burst may include such a fixed bit pattern located on only one side of the base station specific training sequence.

5   Fig. 7 illustrates schematically another embodiment of a dummy burst 700 likewise having a base station specific training sequence 702 approximately in the middle of the burst. In this case, a fixed bit pattern 704a and 704b, respectively, is included on either side of the training

10   sequence 702, which are both related to that specific training sequence in a known manner. Hence, these bit patterns 704a, 704b are also base station specific and will be known to mobile terminals, such that a receiving terminal can more or less utilise the entire dummy burst to detect

15   and identify the base station, and also to measure the link quality and to make a timing measurement, if needed. Thereby, the chance of correct burst detection will be increased further.

         The base station specific bit patterns 704a, 704b

20   have preferably a relatively low cross correlation to all possible training sequences defined in the network, or at least to the present one 702. As in the previous example, a fixed bit pattern may alternatively be located on only one side of the base station specific training sequence 702.

25   Furthermore, synchronisation over an entire dummy burst may be simplified if also the auto correlation property of the entire dummy burst is taken into account when designing the fixed bit patterns in the data fields.

         If at least two modulation forms are used for the

30   broadcast frequency, the fixed bit pattern 604a, 604b, 704a and 704b, respectively, is preferably different for the different modulation forms.

     In the above-described examples of transmission
strategies and burst structures, the risk of burst confusion
for connected terminals is minimised, at the same time burst
detection for measuring terminals is facilitated maximally.
5 More specifically, bursts with base station specific
training sequences are transmitted as far as possible
without introducing confusion risks. This is beneficial for
the burst detection in mobile terminals, which enables good
reception quality (e.g. speech quality), as well as reliable
10 measurements and base station identifications. Being able to
correctly identify base stations, or at least distinguish
between different base stations, is particularly important
when a relatively tight reuse pattern is employed in a
cellular mobile network where several relevant base stations
15 use the same broadcast frequency. Signals received by
measuring terminals will then typically contain
contributions from more than one base station.

     Using bursts with base station specific training
sequences will thus facilitate measurements, since the
20 receiving terminal only needs to receive the burst during
the training sequence interval (although some additional
symbols may be desirable), in contrast to the entire burst,
in order to obtain a correct synchronisation. Timing
estimations will then be successful more often, for the
25 purpose of positioning measurements. In the traditional
dummy bursts with a common fixed bit pattern, the entire
burst must be detected in order to obtain correct
synchronisation due to its poor auto-correlation properties.

     The present invention may be implemented in a
30 computer program product, either directly loadable into the
internal memory of a computer, or stored on a computer
usable medium. The apparatus for performing the inventive

method by means of running said computer program may be located in a base station and/or in a network node controlling plural base stations. Thus, the "intelligence" for determining the content in bursts to be transmitted from

5   a base station in a mobile network may be placed in that base station or in another network node, such as a BSC, or may be distributed in both.

While the invention has been described with reference to specific exemplary embodiments, the description

10   is only intended to illustrate the inventive concept and should not be taken as limiting the scope of the invention. Various alternatives, modifications and equivalents may be used without departing from the spirit of the invention, which is defined by the appended claims.

15